



Insert for Combination preparation tool (Universal Trimming Tool), CELLFLEX® Cable 1 5/8" for connector families OMNI FIT Standard B32 and RAPID FIT 062/072

Product Description

This is an insert for use with the RFS Universal Trimming Tool for the installation of OMNI FIT™ Standard connectors family B32 and RAPID FIT062/072 on all LCF158-50* cables. The special trimming tool improves the cable preparation prior to connector attachment. No further tools are required to prepare the cable for the connector attachment. This is due to the unique design of the Universal Trimming Tool, which combines all necessary functions in one tool. The Universal Trimming Tool comes always pre-equipped with one insert (TRIM-SET-L***-*** for CELLFLEX® cables and TRIM-SET-R***-*** for RADIAFLEX® cables). This special trimming tool series offers the additional advantage to be convertible to different connector families and cable types and sizes (CELLFLEX® cables and RADIAFLEX® cables 1 1/4" and 1 5/8") only by changing the inserts. Different inserts are available as optional items, for references see below or contact your RFS sales contact.



Features/Benefits

- **Universal Trimming Tool concept**
One basic tool can be used for cable sizes 1 1/4" and 1 5/8" only by changing the insert
- **Precision cable preparation tool**
Always exact and repeatable trimming dimensions.
- **Intuitive use of tool**
Easy and precise preparation of cables for connector installation.
- **Long-lasting cutting blades**
Easy to clean, smooth dielectric surface improves IM performance.

Technical Specifications

Product Line	Coaxial Cable Accessories
Product Type	Tool
Transmission Line Type	LCF158
Coaxial Cable Type	Foam Dielectric
Cable Size	1 5/8"
Type of Tool	Combination Cable Preparation Tool
Configuration	Universal Trimming Tool
Spare Part / Useful Accessories	Spare blades : TRIM-B31
Material	Blade Holder: Aluminum Alloy Collet: POM
Length, mm (in)	110 (4.33)
Height, mm (in)	75 (2.95)
Width, mm (in)	75 (2.95)
Package Quantity	1
Weight per piece, kg (lb)	0.33 (0.73)

Notes

Other available inserts to convert the tool for use with other connector series or cable sizes:

- **TRIM-IL114-001** for connectors B32, 062/072 on cable LCFS/UCF114-50
- **TRIM-IL114-D01** for connectors D01 on cable LCFS/UCF114-50
- **TRIM-IL114-C02** for connectors C02 on cable LCFS/UCF114-50
- **TRIM-IL158-D01** for connectors D01 on cable LCF158-50
- **TRIM-IL158-C02** for connectors C02 on cable LCF158-50
- **TRIM-IR114-P01** for all connectors on RADIAFLEX® cables 1 1/4" with copper foil outer conductor except for jacket options JFCLA
- **TRIM-IR158-P01** for all connectors on RADIAFLEX® cables 1 5/8" with copper foil outer conductor except for jacket options JFCLA

Other Documentation

User Manual: [1000008138-03_User Manual TRIM-U-114-158.pdf](http://www.rfsworld.com/1000008138-03_User Manual TRIM-U-114-158.pdf)