



## Waveguide Transition PDR120 to PDR140

Straight waveguide with different waveguide sizes on each end. Hardware and pressure gaskets included.



Picture show example of transitions

## **Technical Features**

STRUCTURE			
Type of Rectangular Waveguide Component		Transition	
Waveguide Size IEC (EIA)		R120 (WR75)	
Flange A		PDR120	
Flange B		PDR140	
Flange Finish		Brass un-plated	
Package Quantity		1	
ELECTRICAL SPECIFICATIONS			
Frequency Range	GHz	11.9 - 15	
Minimum Return Loss (max. VSWR)	dB (VSWR)	32.3 (1.05)	
MECHANICAL SPECIFICATIONS			
Length	mm (in)	38 (1.5)	
MATERIAL			
Material		Brass	
Color		Black	

External Document Links	Notes

TRAN-D120-D140-1-B-004M REV
-----------------------------

REV: A

REV DATE: 27. Nov 12

www.rfsworld.com